


PITFALL (834-5627)

COIN/CREDIT OPTIONS SWITCH SETTING


OPTION		DIP SWITCH #A							
		1	2	3	4	5	6	7	8
1 COIN 1 CREDIT		OFF	OFF	OFF	OFF	OFF	OFF	OFF	OFF
1 COIN 2 CREDITS		ON	OFF	OFF	OFF	ON	OFF	OFF	OFF
1 COIN 3 CREDITS		OFF	ON	OFF	OFF	OFF	ON	OFF	OFF
1 COIN 4 CREDITS		ON	ON	OFF	OFF	ON	ON	OFF	OFF
1 COIN 5 CREDITS		OFF	OFF	ON	OFF	OFF	ON	ON	OFF
1 COIN 6 CREDITS		ON	OFF	ON	OFF	ON	OFF	ON	OFF
2 COINS 1 CREDIT		OFF	ON	ON	OFF	OFF	ON	ON	OFF
3 COINS 1 CREDIT		ON	ON	ON	OFF	ON	ON	ON	OFF
4 COINS 1 CREDIT		OFF	OFF	OFF	ON	OFF	OFF	OFF	ON
2 COINS 3 CREDITS		ON	OFF	OFF	ON	ON	OFF	OFF	ON
2 COINS 1 CREDIT									
4 COINS 2 CREDITS		OFF	ON	OFF	ON	OFF	ON	OFF	ON
5 COINS 3 CREDITS									
6 COINS 4 CREDITS									
2 COINS 1 CREDIT		ON	ON	OFF	ON	ON	ON	OFF	ON
4 COINS 2 CREDITS									
1 COIN 1 CREDIT									
2 COINS 2 CREDITS		OFF	OFF	ON	ON	OFF	OFF	ON	ON
3 COINS 3 CREDITS									
4 COINS 4 CREDITS									
5 COINS 6 CREDITS									
1 COIN 1 CREDIT									
2 COINS 2 CREDITS		ON	OFF	ON	ON	ON	OFF	ON	ON
3 COINS 3 CREDITS									
4 COINS 5 CREDITS									
1 COIN 1 CREDIT		OFF	ON	ON	ON	OFF	ON	ON	ON
2 COINS 3 CREDITS									
1 COIN 1 CREDIT		ON	ON	ON	ON	ON	ON	ON	ON
COIN SWITCH #1		COIN SWITCH #2							

OPTION SWITCH SETTING

OPTION		DIP SWITCH #B							
		1	2	3	4	5	6	7	8
TABLE UPRIGHT		OFF	ON						
ADVERTISE SOUND	OFF		OFF						
	ON		ON						
NUMBER OF PLAYERS	3 MEN			OFF	OFF				
	4 MEN			ON	ON				
	5 MEN			OFF	ON				
	FREE			ON	ON				
SCORE OF ADDITIONAL PLAYERS	20000&50000					OFF			
	30000&70000					ON			
NOT CONTINUE							OFF		
CONTINUE							ON		
GAME DIFFICULTY	NORMAL							OFF	
	HARD							ON	




BARE BD No.
171-5034
171-5054
171-5054-01



BARE BD No.
171-5054-02

44 PIN P=3.96mm

COMPONENT SIDE			SOLDER SIDE
GND	22	22	GND
BLUE	21	21	CMP SYNC
RED	20	20	GREEN
SPEAKER	19	19	SPEAKER
SERVICE SW.	18	18	NOT USED
TEST SW.	17	17	NOT USED
COIN SW 2	16	16	2P START
COIN SW 1	15	15	1P START
1P LEFT	14	14	2P LEFT
1P RIGHT	13	13	2P RIGHT
1P UP	12	12	2P UP
1P DOWN	11	11	2P DOWN
NOT USED	10	10	NOT USED
1P JUMP	9	9	2P JUMP
NOT USED	8	8	NOT USED
NOT USED	7	7	NOT USED
+12V	6	6	NOT USED
COIN METER 1	5	5	COIN METER 2
+5V	4	4	+5V
GND	3	3	GND
	2	2	
	1	1	



SUPPLY VOLTAGES & CURRENT	
VOLTAGE	CURRENT
DC5V	4.1A
DC12V	0.25A